

General Disclaimer


One or more of the Following Statements may affect this Document

- This document has been reproduced from the best copy furnished by the organizational source. It is being released in the interest of making available as much information as possible.
- This document may contain data, which exceeds the sheet parameters. It was furnished in this condition by the organizational source and is the best copy available.
- This document may contain tone-on-tone or color graphs, charts and/or pictures, which have been reproduced in black and white.
- This document is paginated as submitted by the original source.
- Portions of this document are not fully legible due to the historical nature of some of the material. However, it is the best reproduction available from the original submission.

**NASA TECHNICAL
MEMORANDUM**

NASA TM X-52626

NASA TM X-52626



RICHARDSON DUSHMAN EQUATION NOMOGRAPH

by Arthur L. Smith and Roland Breitwieser
Lewis Research Center
Cleveland, Ohio
June, 1969

N69-33741

FACILITY FORM 602	(ACCESSION NUMBER)	(THRU)
	11	1
	(PAGES)	(CODE)
	TMX 52626	10
	(NASA CR OR TMX OR AD NUMBER)	(CATEGORY)

NASA TM X-52626

RICHARDSON DUSHMAN EQUATION NOMOGRAPH

by Arthur L. Smith and Roland Breitwieser

Lewis Research Center
Cleveland, Ohio

NATIONAL AERONAUTICS AND SPACE ADMINISTRATION

ABSTRACT

This report presents nomographic solutions to the Richardson Dushman equation. The nomographs have been scaled to meet the emission conditions of the emitter and the back emission condition of the collector. Values of work functions are presented at 20° K intervals in the temperature range from 600° to 2500° K. The current density ranges from 1×10^{-7} to 1×10^2 . The reading error of work function was determined to be less than 0.01 V.

RICHARDSON DUSHMAN EQUATION NOMOGRAPH

by Arthur L. Smith and Roland Breitwieser

Lewis Research Center

SUMMARY

E-5137 This report presents nomographic solutions to the Richardson Dushman equation. The nomographs have been scaled to meet the emission conditions of the emitter and the back emission conditions of the collector. Values of work functions are calculated at 20° K intervals in the temperature range from 600° to 2500° K. The current density ranges from 1×10^{-7} to 1×10^2 . The reading error of work function was found to be less than 0.01 V.

INTRODUCTION

This memorandum presents nomographic solutions to the Richardson Dushman (RD) equation^{1, 2} found to be convenient in treating electron emission of thermionic converters and similar devices. The nomographs have been scaled to meet the conditions of the emitter (fig. 1) and the back emission conditions of the collector (fig. 2).

The effective work function^{3, 4, 5} is used in this presentation, that is, the pre-exponential constant is set equal to the theoretical value of 120.1. The surface reflection coefficient is assumed to be zero, the common practice for metallic electrodes. The RD equation then reduces to

$$J = 120.1 T^2 \exp - \frac{e\phi}{kT}$$

where

- J current density in amp/sq cm
- T electrode temperature, $^{\circ}\text{K}$
- e electron charge in Coulombs
- φ the effective work function in volts
- k the Boltzmann constant in $\text{J}/^{\circ}\text{K}$

Although the RD equation describes electron emission under idealized conditions rarely met experimentally, the effective work function is convenient to use in comparing the relative emission capabilities of surfaces. Also, the use of this thermodynamic equilibrium expression is of value in the heat engine analyses of energy conversion devices.


The solution of the RD equation is usually presented in the form of tables⁶ and charts^{3, 7}. We have found the nomographs provide a reasonably accurate condensation of this information. The reading error of φ was determined to be less than 0.01 V. Experimental values of work functions usually involve an uncertainty greater than ± 0.05 V, thus the figures above should be adequate for many uses.

REFERENCES

1. Richardson, O. W.: Electron Theory of Matter. Phil. Mag., vol. 23, Apr. 1912, pp. 594-627.
2. Dushman, S.: Electron Emission from Metals as a Function of Temperature. Phys. Rev., vol. 21, June 1923, pp. 623-636.
3. Hensley, Eugene B.: Thermionic Emission Constants and Their Interpretations. J. Appl. Phys., vol. 32, no. 2, Feb. 1961, pp. 301-308.
4. Herrings, Congers; and Nichols, M. H.: Thermionic Emission. Rev. Mod. Phys., vol. 21, no. 2, Apr. 1949, pp. 185-270.

5. Nottingham, W. B.: Thermionic Emission. Handbuch der Physik. Vol. 21. S. Flügge, ed., Springer-Verlag, Berlin, 1956, p. 1.
6. Read, P. L.: Tables of the Effective Work Function. Rep. 64-RL-3605E, General Electric Co., Mar. 1964.
7. Jansen, C. G. J.; and Loosjes, R.: Graphs for a Rapid Calculation of the Work Function of Thermionic Emission. Philips Res. Repts., vol. 8, no. 2, Apr. 1953, pp. 81-90.

E-5137



FOLDOUT FRAME


Figure 2. - Emission current density based on the solution of the



on of the Richardson Dushman equation for various effective work function (ϕ) and electrode temperatures (T).

FOLDOUT FRAME

J (amp/cm²)



ve work function (ϕ) and electrode temperatures (T).

FOLDOUT FRAME

E-5137





Figure 1. - Emission current density based on the solution of the


ϕ (Volt)



Current density based on the solution of the Richardson Dushman equation for various effective work functions (ϕ) and electrode temperatures (T).

FOLDOUT FRAMES

J (amp/cm²)



for various effective work functions (ϕ) and electrode temperatures (T).